

NLS-FR20

Desktop Barcode Scanner



Designed primarily for such applications as electronic tickets/coupons, mobile marketing and office automation, the NLS-FR20 desktop barcode scanner is able to read barcodes from paper and mobile phones.

Features

Digital Barcode Data Capture

Capable of reading 1D and 2D barcodes off mobile phones.

Printed Barcode Data Capture

Capable of reading 1D and 2D barcodes printed on paper.

Swift Scanning

Delivers effortless, snappy and accurate reading of barcodes on various mobile phone LCD screens with different contrast ratios, colors and reflectance.

Easy to Use

Simple configuration by scanning the programming barcodes provided in the user guide.

NLS-FR20 Specifications

NEO I NZO Opecinications						
Performance						
Processor		IOTC 0370 CHIP				
Image Sensor		640×480 CMOS				
Interface		RS-232 (9.6~115.2Kbps) / USB 1.1 (HID-KBW, HID-POS)				
	2D	PDF417, Data Matrix, QR Code				
Cumbalagias		EAN-13, EAN-8, UPC-A, UPC-E, ISSN, ISBN, Codabar, Code 128, Code 93, ITF-6, ITF-14, Interleaved 2 of 5, Industrial 2 of 5, Standard 2 of 5, Matrix 2 of 5, GS1 Databar (RSS-Expand, RSS-Limited, RSS-14), Code 39, Code 11, MSI-Plessey, Plessey				
Symbologies	1D					
Scan Mode		Sense mode, Continuous mode				
Resolution		10mil				
Light Source		White LED				
Scan Window		52mm×69mm				
PCS		≥30%				
FOV		Diagonal: 68°, Horizontal: 42°, Vertical: 54°				
Mechanical/Ele	ectrical					
Power Consumption		1W (max.)				
Notification		Beep, LED indicator				
Dimensions (L x W x H)		127.3×111.5×94mm				
Weight		300g				
Environmental						
Operating Temperature		-10°C - +50°C				
Storage Temperature		-20°C - +60°C				
Humidity		5% - 95% (non-condensing)				
Ambient Light		0 ~ 100,000 LUX				
Certifications						

FCC Part15 Class B, CE EMC Class B

Accessories					
Cable	RS-232 Cable	Equipped with a power connector; used to connect the scanner to a host device.			
	USB Cable	Used to connect the scanner to a host device.			
Power Adapter		Used to provide power for the scanner.			
		Output: DC5V, 0.5A; Input: AC100~240V, 50~60Hz.			

Contact Us

Newland China	Newland Europe	Newland Taiwan	Newland North America
+86-400-608-0591	+31(0)-345-87-0033	+886-2-7731-5388	+1-510-490-3888
marketing@nlscan.com	info@newland-id.com	info@newland-id.com.tw	info@newlandna.com

www.nlscan.com

